



The  
Patent  
Office


PCT/GB 00 / 001 / 4



INVESTOR IN PEOPLE

GB00/174

4




The Patent Office  
Concept House  
Cardiff Road  
Newport  
South Wales  
NP10 8QQ

I, the undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation & Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents as originally filed in connection with the patent application identified therein.

In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1980 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.

In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.

Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.



Signed

*W. Evans*

Dated 3<sup>rd</sup> February, 2000.

**PRIORITY  
DOCUMENT**

SUBMITTED OR TRANSMITTED IN  
COMPLIANCE WITH RULE 17.1(a) OR (b)

An Executive Agency of the Department of Trade and Industry

**BEST AVAILABLE COPY**



1/77  
(Rev. 1/77)



1/77

# Request for grant of a patent

(See the notes on the back of this form. You can also get an explanatory leaflet from the Patent Office to help you fill in this form)

The Patent Office

Cardiff Road  
Newport  
Gwent NP9 1RH

1. Your reference

HL71607/000/DCO

2. Patent application number

(The Patent Office will fill in this part)

9901491.2

25JAN99 E420131-7 D02847  
P01/7700 0.00 - 9901491.2

3. Full name, address and postcode of the or of each applicant (underline all surnames)

University of Bristol  
Senate House  
Tyndall Avenue  
Bristol  
BS8 1TH  
United Kingdom

Patents ADP number (if you know it)

If the applicant is a corporate body, give the country/state of its incorporation

793181001

4. Title of the invention

RECEIVER

5. Full name of your agent (if you have one)

Haseltine Lake & Co.

"Address for service" in the United Kingdom to which all correspondence should be sent (including the postcode)

Imperial House  
15-19 Kingsway  
London WC2B 6UD

34001

Patents ADP number (if you know it)

6. If you are declaring priority from one or more earlier patent applications, give the country and the date of filing of the or of each of these earlier applications and (if you know it) the or each application number

Country

Priority application number  
(if you know it)

Date of filing  
(day/month/year)

7. If this application is divided or otherwise derived from an earlier UK application, give the number and the filing date of the earlier application

Number of earlier application

Date of filing  
(day/month/year)

8. Is a statement of inventorship and of right to a grant of patent required in support of this request? (Answer "Yes" if:

Yes

- a) any applicant named in part 3 is not an inventor, or
  - b) there is an inventor who is not named as an applicant, or
  - c) any named applicant is a corporate body.
- See note (d))

**Patents Form 1/77**

9. Enter the number of sheets for any of the following items you are filing with this form. Do not count copies of the same document

Continuation sheets of this form 0

Description 10 ✓

Claim(s) 3 ✓

Abstract 0

Drawing(s) 4 *4450*

10. If you are also filing any of the following,

Priority documents 0

Translations of priority documents 0

Statement of inventorship and right to a grant of patent (Patents Form 7/77) 0

Request for preliminary examination and search (Patents Form 9/77) 0

Request for substantive examination (Patents Form 10/77) 0

Any other documents (please specify) 0

11.

I/We request the grant of a patent on the basis of this application

Signature

Date

22 January 1999

12. Name and daytime telephone number of person to contact in the United Kingdom

Mr. D.C. O'Connell

[0117] 9103200

**Warning**

*After an application for a patent has been filed, the Comptroller of the Patent Office will consider whether publication or communication of the invention should be prohibited or restricted under Section 22 of the Patents Act 1977. You will be informed if it is necessary to prohibit or restrict your invention in this way. Furthermore, if you live in the United Kingdom, Section 23 of the Patents Act 1977 stops you from applying for a patent abroad without first getting written permission from the Patent Office unless an application has been filed at least 6 weeks beforehand in the United Kingdom for a patent for the same invention and either no direction prohibiting publication or communication has been given, or any such direction has been revoked.*

**Notes**

- If you need help to fill in this form or you have any questions, please contact the Patent Office on 0645 500505.*
- Write your answers in capital letters using black ink or you may type them.*
- If there is not enough space for all the relevant details on any part of this form, please continue on a separate sheet of paper and write "see continuation sheet" in the relevant part(s). Any continuation sheet should be attached to this form.*
- If you have answered "Yes" Patents Form 7/77 will need to be filed.*
- Once you have filled in the form you must remember to sign and date it.*
- For details of the fee and ways to pay please contact the Patent Office.*

RECEIVER

This invention relates to a receiver, and in particular to an OFDM receiver, and to an adaptive  
5 equalizer for use in such a receiver and to a method of training the equalizer.

The European digital terrestrial television standard, DVB-T, specifies orthogonal frequency division multiplexing, OFDM as the modulation scheme.

10 In conventional OFDM systems, multipath radio transmission channels cause delay spread distortion of the transmitted signal. Although adaptive equalizers can be used in many applications to cancel out delay spread distortion, existing designs for OFDM receivers  
15 and adaptive equalizers are generally incompatible, although it has been proposed to use a number of equalizers acting in parallel on respective sub-bands of the OFDM signal.

Therefore, existing designs for OFDM systems  
20 employ guard intervals to combat the effects of delay spread. Each transmission period includes a period during which useful information is transmitted, and a guard interval, during which no useful information is transmitted. Thus, use of a guard interval reduces  
25 efficiency of the transmission, and less data can be transmitted within a given radio frequency bandwidth.

The present invention relates to an OFDM receiver including an adaptive equalizer, which attempts to overcome the incompatibility of existing designs of  
30 OFDM receivers and adaptive equalizers.

According to a first aspect of the present invention, there is therefore provided a receiver as defined in claim 1.

According to a second aspect of the present  
35 invention, there is therefore provided an equalizer as defined in claim 6.

According to a third aspect of the present invention, there is therefore provided a method as defined in claim 7.

5 For a better understanding of the present invention, reference will now be made to the accompanying drawings, in which:-

Figure 1 shows a first receiver in accordance with the invention;

10 Figure 2 shows a first equalizer in accordance with the invention;

Figure 3 shows a second equalizer in accordance with the invention;

Figure 4 shows a second receiver in accordance with the invention.

15 DETAILED DESCRIPTION OF PREFERRED EMBODIMENTS

As Shown in Figure 1, a transmitted analog OFDM symbol is received over a radio frequency channel 2 having unknown and time-varying characteristics, and is subject to the addition of noise.

20 The receiver therefore takes an input signal  $y_1'(t)$  in an input device 4, where it is demodulated, A-D converted and down-sampled to give a time domain vector  $y'(n,1)$ . The received sequence  $y'(n,1)$  is filtered by an adaptive equalizer 6 to produce a time-domain  
25 sequence  $z'(n,1)$ .

The time domain sequence output from the equalizing filter 6 is input to a guard extraction device 8 to form an output  $z(n,1)$ . An advantage of the present invention is that the need for a guard interval  
30 may be reduced or eliminated. The guard extraction device 8 is therefore required only if it is needed if a guard interval is used by the transmitter which is in use.

A Fast Fourier Transform (FFT) 10 is then applied  
35 to  $z(n,1)$  to produce a frequency domain vector  $Z(k,1)$ .

In this embodiment of the invention, the frequency

domain vector is supplied to a channel estimator 12 which derives an estimation of the radio channel's frequency response and compensates according to this estimate. In an alternative embodiment, the channel estimator may be omitted.

The vector is then supplied to an output device 14 to produce a data output. The output device 14 may be nothing more than a hard limiter, putting the data into a useable form. However, any interleaving, coding, signal mapping or other error control strategies applied in the transmitter are reversed in the output device 14 and exploited to correct any errors and produce the output data sequence. The output data, which is the best possible estimate of the data content of the transmitted signal is then applied to a feedback loop, and processed to form the best possible estimate of the transmitted sequence. Specifically, the data output is applied to a device 16 which interleaves, codes and maps the data in an identical manner to that performed at the transmitter to produce the frequency domain sequence  $W(k, l)$ .

The frequency domain sequence is input to an inverse Fourier transform device 18 and the output  $w(n, l)$  of this device is applied to a guard interval insertion device 20 to insert a guard interval corresponding to any that was added in the transmitter to generate a sequence  $w'(n, l)$ . In effect, the data output is processed in the feedback loop to effectively attempt to reconstruct the OFDM symbol that was generated at the transmitter, and hence  $w'(n, l)$  is an estimate of the transmitted sequence  $x'(n, l)$ .

The estimate  $w'(n, l)$  is then input to the equalizing filter 6 to enable decision directed adaptation of the tap coefficients thereof.

Each updated estimate of an OFDM symbol, made up of a number of sub-symbols, is available to the

equalizer only after all sub-symbols of one OFDM symbol have been received.

Figure 2 shows the equalizer of the present invention. As is generally conventional, the equalizer consists of two shift register sections: a feedforward section 32 that stores future transmission symbols and the current transmission symbol and a feedback section 34 that stores previous transmission symbols. The length of the feedforward section is  $(J_1+1)$  symbols and the length of the feedback section is  $J_2$  symbols. The received sequence  $y'(n,1)$  is input, the value of each stored symbol is multiplied by a tap coefficient  $c(j)$ , and the results are summed to form the equalizer output  $z'(n,1)$ .

The tap coefficients  $c(j)$  are updated according to the LMS adaptation algorithm. As is known, the LMS algorithm adapts the equalizer taps according to the error measure between the equalizer output symbols and an estimate of the transmitted symbols. The estimate of the transmitted symbols can be achieved either by means of a training sequence or by decision directed adaptation.

Adaptation according to a training sequence requires the transmission of symbols of which the equalizer has prior knowledge. This training mode allows adaptation according to an error free estimate of transmitted symbols but results in no data throughput.

Decision directed adaptation feeds back output data to estimate the transmitted symbols. This estimate is not necessarily error free but does allow for data throughput.

In practice, the two techniques are combined. An initial training sequence approximately adapts the equalizer and reduces equalizer output error sufficiently that decision directed adaptation may



provide an adequate error measurement for further adaptation. During decision directed adaptation the equalizer further adapts both to 'fine tune' its action and to track any relatively small time variation in the radio channel.

The equalizer of Figure 2 is generally similar to a conventional equalizer, although there are differences as follows:-

Symbols input to the feedback register 32 during decision directed operation do not come directly from the decision device but rather from the feedback vector.

Symbols used to calculate error during decision directed operation come similarly from the feedback vector rather than direct from the decision device.

Additional buffers 36, 38 for both feedforward and feedback sections further store past symbols beyond the duration of the feedforward/feedback sections. These additional stored values are required for decision directed adaptation

During decision directed mode the tap coefficients are not updated at intervals of the sub-symbol period, but rather at the OFDM symbol period, regarding one OFDM symbol as made up a group of sub-symbols.

However, the LMS calculation is performed in the LMS calculation processor 40 to calculate adjustments corresponding to intervals of the sub-symbol period with the sum of all calculated adjustments being made at intervals of the OFDM symbol period.

The equalizer output may be directly input to the feedback section thereof.

These additional features, which apply during a decision directed (or data derived) operation, enable the equalizer to operate within the OFDM receiver architecture.

More detailed explanation of all these features is

given below.

Since the equalizer operates on the received time domain sequence its output is also a time domain sequence. Data in the OFDM modem is in the frequency domain and hence the equalizer output must be Fourier Transformed (with any guard interval first being removed) prior to the decision process. Thus, the output of the equalizer cannot be applied directly to the decision device. Similarly the decision device output cannot be fed back directly to the equalizer. The feedback vector is fed back instead. If the equalizer is adapting according to a training sequence this is irrelevant, since the training sequence itself is an error free estimate of the transmitted sequence and can be input to the equalizer's feedback section. Furthermore, the decision device output cannot be used to calculate the output error used in the LMS adaptation algorithm and the feedback vector is again used instead.

The additional symbol buffering and the changes to the adaptation process in decision directed mode are necessary since the parallel transmission undertaken in OFDM results in the group post-decision data sub-symbols making up one OFDM symbol being simultaneously output at intervals of the OFDM symbol period. (By contrast, a single carrier system outputs individual symbols at intervals of the symbol period.) This restriction imposed by the parallel transmission prevents decision directed adaptation during OFDM symbols. It also prevents feedback values becoming available to the equalizer until the end of the OFDM symbol.

Therefore, instead of adapting the equalizer with each transmission sub-symbol, all transmission symbols forming the OFDM symbol are clocked through the equalizer with the tap coefficients remaining constant

and the equalizer output is input directly into the feedback section. At the end of each OFDM symbol the past and future transmission symbols that were stored in the feedforward and feedback sections at the start of the OFDM symbol are recovered from the buffers. Since the tap coefficients remain constant throughout the OFDM symbol the equalizer is effectively returned to its state at the start of the OFDM symbol. The OFDM symbol is then clocked into the equalizer once more with the feedback OFDM symbol now available both for determination of error and input to the feedback section. This process enables the adaptation steps that had not previously taken place to be completed and replaces the fed back output symbols with post decision estimates of the transmitted symbols as provided by the feedback OFDM symbol.

This method of operation described above allows both the feedforward and feedback stages of the equalizer to have numbers of taps which are integer multiples of the length of the extended OFDM symbol, which is considered to be  $(N+M)$ , with  $N$  the number of transmission symbols in the useful period of an OFDM symbol, and  $M$  the number of transmission symbols in the guard period. In this illustrated embodiment, these numbers of taps are equal to the length of the extended OFDM symbol.

The equalizer output is then given by:-

$$z'(n,l) = \sum_{j=-J_1}^{-J_1+M} c(j) y'((n-j-(N+M)), l+1) + \sum_{j=-J_1+M+1}^0 c(j) y'((n-j), l) \\ + C_{\text{out}}(n) \sum_{j=1}^N c(j) z'((n-j), l) + \sum_{j=N+1}^{J_2} c(j) w'((n+(N+M)-j), l-1)$$

where:

$$C_{\text{out}}(n) = 0 \quad \text{for} \quad n = 0$$

and:

$$C_{\text{out}}(n) = 1 \quad \text{for} \quad n \neq 0$$

The equalizer is then adapted according to the LMS algorithm, which in this case is defined as follows:-

During Training Mode:

$$c(j, n+1, l) = c(j, n, l) + \Delta \varepsilon'(n, l) y^{**}((n-j-(N+M)), l+1)$$

for  $-J_1 \leq j \leq -J_1 + n + 1$

$$c(j, n+1, l) = c(j, n, l) + \Delta \varepsilon'(n, l) y^{**}((n-j), l)$$

for  $-J_1 + n + 2 \leq j \leq 0$

$$c(j, n+1, l) = c(j, n, l) + \Delta \varepsilon'(n, l) x^{**}((n-j), l)$$

for  $1 \leq j \leq n$

$$c(j, n+1, l) = c(j, n, l) + \Delta \varepsilon'(n, l) x^{**}((n+(N+M)-j), l-1)$$

for  $n+1 \leq j \leq J_2$

$$\varepsilon'(n, l) = x'(n, l) - z'(n, l)$$

During Decision Directed Operation

$$c(j, n, l+1) = c(j, n, l) + C_{\beta}(j) \sum_{n=0}^{N+M-j-1} \Delta \varepsilon'(n, l) y'((n-j), l) + \sum_{n=N+M+j}^{N+M-1} \Delta \varepsilon'(n, l) y'((n-(N+M)-j), l+1)$$

for  $-J_1 \leq j \leq 0$

$$c(j, n, l+1) = c(j, n, l) + \sum_{n=0}^{j-1} \Delta \varepsilon'(n, l) w'((n+(N+M)-j), l-1) + C_{\beta}(j) \sum_{n=j}^{N+M-1} \Delta \varepsilon'(n, l) w'((n-j), l)$$

for  $1 \leq j \leq J_2$

$$\varepsilon'(n, l) = w'(n, l) - z'(n, l)$$

where:

$$C_g(j) = 0 \quad \text{for} \quad -j = N + M$$

and:

$$C_g(j) = 1 \quad \text{for} \quad -j \neq N + M$$

$$C_g(j) = 0 \quad \text{for} \quad j = N + M$$

and:

$$C_g(j) = 1 \quad \text{for} \quad j \neq N + M$$

$\Delta$  Equalizer step constant

$c(j, n, l)$  Equalizer tap vector in OFDM system

$\epsilon(n, l)$  Equalizer output error vector in OFDM system

Figure 3 shows an alternative equalizer in accordance with the invention. It corresponds generally to that of Figure 2, except that the symbols input to the equalizer's feedback section 34 are zero symbols. This prevents the feedback of noise bearing symbols into the equalizer but, as a consequence, the equalizer no longer cancels delay spread distortion from within the same OFDM symbol. However this will still allow for an effective transmission strategy since, for example, where a guard interval is employed, delay spread interference within the same OFDM symbol does not cause inter-carrier interference (ICI). Thus, an equalizer with zero symbol feedback may be combined with a channel estimation process to achieve cancellation of delay spread distortion without the need to feed back pre-decision transmission symbols.

Thus, in Figure 3, compared with Figure 2, the feedback path from the equalizer output directly to the feedback section is replaced by a zero symbol source.

The equalizer output then becomes:-

$$C_{out}(n) = 0, \text{ for all } n.$$

The method of tap adaptation in the equalizer of figure 3 is the same as that described above with reference to Figure 2.

The equalizer is no longer required to cancel all delay spread distortion and hence the equalizer output is not expected to approximate the transmitted sequence. The receiver is therefore as shown in Figure 4, as the feedback vector must be adjusted to compensate the uncombated distortion. This is achieved by reversing the channel compensation process in the feedback path. Thus the channel estimate produced by the channel estimator 12 is applied in reverse to the output of mapping and interleaving device 16. This achieves a feedback vector which is suitably adjusted.

There is thus described a receiver, and an equalizer, which allow adaptive equalization of OFDM signals, with a consequent improvement in the noise in the received signals.

CLAIMS

1. An OFDM receiver, comprising:
  - a received signal processor, for demodulating, A-D  
5 converting, and down-sampling received signals to form  
a time domain digital signal vector;  - an equalizer, having at least a feedback section  
and having a plurality of tap coefficients, the  
equalizer acting on the time domain digital signal  
10 vector to form a filtered time domain sequence;  - a Fast Fourier Transform processor, for acting on  
the filtered time domain sequence to form a frequency  
domain vector;  - an output device, for converting the frequency  
15 domain vector into an output data signal;  - an inverse Fast Fourier Transform processor, for  
acting on the output data signal to form an estimate of  
the transmitted sequence;  - wherein the estimate of the transmitted sequence  
20 is supplied as an input to the equalizer to enable  
decision directed adaptation of the tap coefficients  
thereof, and further as an input to the feedback  
section of the equalizer.
2. An OFDM receiver as claimed in claim 1,  
25 further comprising:
  - a guard extraction device, for extracting any  
guard sequence from the filtered time domain sequence  
before processing by the Fast Fourier Transform  
processor; and  
30 a guard insertion device, for inserting a guard  
interval, corresponding to that removed by the guard  
extraction device, into the estimate of the transmitted  
sequence supplied by the inverse Fast Fourier Transform  
processor.
3. An OFDM receiver as claimed in claim 1,  
35 further comprising:

a channel estimator, for compensating the frequency domain vector to produce a compensated frequency domain vector.

4. An OFDM receiver as claimed in claim 1,  
5 wherein the output device comprises means for exploiting and cancelling any error control strategies applied in a transmitter of the received signals, and further comprising:

means for reapplying to the output data signal any  
10 error control strategies cancelled in the output device.

5. An OFDM receiver as claimed in claim 4, wherein the output device comprises means for deinterleaving the compensated frequency domain vector.

15 6. An OFDM receiver as claimed in claim 4, wherein the output device comprises means for demapping the compensated frequency domain vector.

7. An adaptive decision feedback equalizer, comprising:

20 a first input, for a received signal comprising a plurality of symbols, the symbols representing an OFDM signal, each OFDM symbol comprising a plurality of sub-symbols per OFDM symbol period;

a feedforward stage, comprising a first number of  
25 taps and corresponding tap coefficients;

a feedback stage, comprising a second number of taps and corresponding tap coefficients;

a first buffer, for storing past symbols beyond symbols present in the feedforward stage;

30 a second buffer, for storing past symbols beyond symbols present in the feedback stage;

a correction algorithm processor, for updating tap coefficients of taps in the feedback stage and the feedforward stage at intervals of the OFDM symbol  
35 period.

8. A method of adapting coefficients of an



adaptive equalizer, the equalizer comprising:

5 a first input, for a received signal comprising a plurality of symbols, the symbols representing an OFDM signal, each OFDM symbol comprising a plurality of sub-symbols per OFDM symbol period;

a second input, for receiving a feedback signal comprising an estimate of a transmitted signal;

a feedforward stage, comprising a first number of taps and corresponding tap coefficients;

10 a feedback stage, comprising a second number of taps and corresponding tap coefficients;

a first buffer, for storing past symbols beyond symbols present in the feedforward stage;

15 a second buffer, for storing past symbols beyond symbols present in the feedback stage; and

a correction algorithm processor, for updating tap coefficients of taps in the feedback stage and the feedforward stage at intervals of the OFDM symbol period, the method comprising:

20 supplying the feedback signal to the second input once per symbol period;

calculating required corrections to the tap coefficients corresponding to intervals of the sub-symbol period; and

25 updating the tap coefficients of the taps at intervals of the OFDM symbol period based on all calculated corrections obtained during each said period.

9. A method as claimed in claim 8, further  
30 comprising outputting an equalized signal at intervals of the symbol period.

**THIS PAGE BLANK (USPTO)**




FIGURE 1

**THIS PAGE BLANK (USPTO)**




FIGURE 2

**THIS PAGE BLANK (USPTO)**




FIGURE 3

~~BEST AVAILABLE COPY~~

THIS PAGE BLANK (USPTO)






FIGURE 4

PCT/GB00/0004

24<sup>th</sup> January '00

Haseltine Lake & Co.

**THIS PAGE BLANK (USPTO)**

**BEST AVAILABLE COPY**

**This Page is Inserted by IFW Indexing and Scanning  
Operations and is not part of the Official Record**

## **BEST AVAILABLE IMAGES**

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ **BLACK BORDERS**
- ☐ **IMAGE CUT OFF AT TOP, BOTTOM OR SIDES**
- ☐ **FADED TEXT OR DRAWING**
- ☐ **BLURRED OR ILLEGIBLE TEXT OR DRAWING**
- ☐ **SKEWED/SLANTED IMAGES**
- ☐ **COLOR OR BLACK AND WHITE PHOTOGRAPHS**
- ☐ **GRAY SCALE DOCUMENTS**
- ☐ **LINES OR MARKS ON ORIGINAL DOCUMENT**
- ☐ **REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY**
- ☐ **OTHER:** \_\_\_\_\_

**IMAGES ARE BEST AVAILABLE COPY.**

**As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.**

